

# EXCEL-2

## EMERGENCY LIGHT & L.E.D. EXIT SIGN COMBINATION

*The EXCEL-2 (EXC2) combo is a great energy and cost saving approach to meeting egress lighting requirements. Commercial, retail and industrial facilities that require battery back-up emergency exit signs as well as emergency lighting.*

### FEATURES

- Combo units include all the features of the EXCEL emergency lights and exit signs.
- Injection molded, V-O flame retardant, high impact, thermoplastic housing available in black or white.
- Available with high powered 5 watt, MR-16 halogen lamps.
- Meets or exceeds all state and local codes, tested and certified to UL924, ETL listed.
- Ultra-bright LED lamps consume less than 2 watts.
- LED lamp life is rated at 25 years.
- Utilizes a premium Ni-cad battery.



### OPERATION

Whenever normal utility power fails, the internal solid state transfer switch automatically connects the battery to the lamp heads providing a minimum of 90 minutes of light. When normal utility power is restored, recharging of the battery is initiated by an automatic, solid state, two-rate charger, which includes current limiting and temperature compensation to assure that optimum recharge is achieved. A fully discharged battery will be fully recharged within 12 hours.

SIGN SERIES	WATTS	HEAD TYPE	COLOR	# OF FACES	SIGN COLOR
EXC2	11    27	X MR 16	R RED	U UNIVERSAL	W WHITE
EXCELSERIES	18    32		G GREEN		B BLACK

### WARRANTY

The EXCEL fixture and battery are warranted to be free from defects for a period of one year from date of purchase. The battery is covered by a 5 year pro-rated warranty.

### AGENCY APPROVAL

Meets the illumination requirement of NFPA Life Safety Code 101, 5-10.2.2. Certified and tested to UL924. ETL listed.

